Fysetc Catalyst Bullant

Übersicht

	Catalyst	Bullant
Repo	https://github.com/FYSETC/Catalyst_Kit_V2.0	https://github.com/FYSETC/FYSETC_Bullant_V1.0
Image	https://github.com/FYSETC/Catalyst_Kit_V2.0/blob/449f8a4ea78f707c273e316bcebbfdf13e400e57/software/update_voron0.2_20240108.rar https://github.com/FYSETC/FYSETC-Voron-0.2-Pro/tree/main/0.2%20R1%20V1.1	https://github.com/FYSETC/FYSETC_Bullant_V1.0/blob/90d78536b823cc0e31b075f60f8dc90145677ea5/software/Bullant_Armbian_OS_Klipper_Build_in_V1.0.rar
Hostname	maixsense	maixsense
User / Password	Default: linaro/linaro, root/root	Default: bullant/armbian, root/armbian
Network	1Gb Kein Autonegotiation auf 100mBit	100mBit
Schaltplan	https://github.com/FYSETC/Catalyst_Kit_V2.0/blob/449f8a4ea78f707c273e316bcebbfdf13e400e57/hardware/CATALYST%20V2.0%20SCH.pdf	https://github.com/FYSETC/FYSETC_Bullant_V1.0/blob/90d78536b823cc0e31b075f60f8dc90145677ea5/Bullant%20V1.0%20SCH.pdf
Pinout	https://github.com/FYSETC/Catalyst_Kit_V2.0/blob/449f8a4ea78f707c273e316bcebbfdf13e400e57/hardware/CATALYST%20V2.0%20PinsOut.png https://github.com/FYSETC/Catalyst_Kit_V2.0/blob/449f8a4ea78f707c273e316bcebbfdf13e400e57/hardware/CATALYST%20V2.0%20%E4%BD%8D%E5%8F%B7%E5%9B%BE.pdf	https://github.com/FYSETC/FYSETC_Bullant_V1.0/blob/90d78536b823cc0e31b075f60f8dc90145677ea5/Bullant%20V1.0%20PNOUT.pdf
CPU / RAM	CM68 core based on RK3568 Quad Core 2GB Ram	Allwinner R329 Dual-Core Cortex-A53 ARM CPU□Sip 256MB DRAM
eMMC Storage	32GB	-
USB	2x USB3.0	1x USB2.0
µController	STM32F446	RP2040
Treiber	TMC2209	TMC2209 + GC6609
RGB	vorhanden	vorhanden
Fans	3x geregelt bis 24V	1 Fan
Temp	3x Temp	1x Temp
CAN Bus	vorhanden	-
Sonstiges	I2C, SPI, extra 2x UART	

Besonderheiten

- **M36 Boards nicht Pinkompatibel** (Anschluss)
  - anderes Pinout am Stecker aber gleiche Stecker / Buchse
- keine root Partition mit armbian Konfig
- Image für Catalyst laut Pi Imager defekt weil Bytesumme nicht durch 512 teilbar
- Catalyst Board geht bei 100MBit Netzwerk nicht Online!!
- Zugriff auf Bullant per seriellem Port (für Init) → unpraktisch
- Bullant macht direkt Update nach Erststart → CPU geblockt
- installiertes `octoeverywhere` → Remote Access
- Update CM68
  - plugin the USB3.0 A-A cable into the interface on the upper layer of the blue USB3.0 socket,
  - open the “RKDevTool_Release”,
  - hold the recovery button, click the reset button, when the RKDevTool found device, release the 2 buttons
  - Click the Upgrade Firmware tab, click the Firmware button to select the firmware, and click the Upgrade button to upgrade
  - Wait for the upgrade to complete. Remember not to cut off the power or unplug the data cable during the process, otherwise the upgrade will fail or even damage the CM68.

Linux Lookaround

- `sudo apt update && sudo apt upgrade -y && sudo apt install -y git silversearcher-ag wavemon hexedit sudoku tcpdump iptraf mc htop dcfldd nano usbutils ranger tldr ncdu can-utils multitail fd-find lsof x11vnc terminator minicom cutecom joystick jstest-gtk && mkdir -p ~/.local/share && tldr -u`
- `cat /etc/os-version`
- `uname -a`
- `free`, `htop` → Systemauslastung

Doom compilieren (chocolate)

- basierend auf https://www.chocolate-doom.org/wiki/index.php/Building_Chocolate_Doom_on_Debian
- `sudo apt install -y gcc make libsdl2-dev libsdl2-net-dev libsdl2-mixer-dev automake autoconf libtool git pkg-config`
- `git clone https://github.com/chocolate-doom/chocolate-doom.git`
- `cd chocolate-doom && ./autogen.sh`
- `make -j4`
- `sudo make install`

From:
https://www.drklipper.de/ - **Dr. Klipper Wiki**

Permanent link:
https://www.drklipper.de/doku.php?id=klipper_faq:sbcs:fysetc_catalyst_bullant&rev=1715700339

Last update: **2024/05/14 17:25**